

# Operational Experience and Results from the S-DALINAC \*

H. Genz, H.-D. Gräf, J. Horn, V. Huck, K.D. Hummel, M. Knirsch,  
 C. Lüttge, A. Richter, T. Rietdorf, K. Rühl, P. Schardt, E. Spamer,  
 A. Stiller, F. Thomas, O. Titze, J. Töpper and H. Weise  
 Institut für Kernphysik, TH-Darmstadt  
 Schloßgartenstr.9, D-6100 Darmstadt

## Abstract

In December 1990 the superconducting cw-electron-accelerator S-DALINAC at Darmstadt for the first time produced a 75 MeV electron beam using all of its components: two recirculations and three passes through the linac. The successful operation of the entire accelerator was the result of several developments. (i) Four new cavities fabricated from RRR280 niobium had been installed together with newly developed coarse and fine tuners. (ii) All eleven superconducting cavities were operated by a micro processor controlled rf-system. (iii) The path length of the two recirculations had been adjusted manually for the correct reinjection phase into the main linac. First experiments using this beam (test of the new Q-CLAM electron spectrometer and channeling radiation experiments) were performed during a running period from January until May 1991. During a shutdown in summer 1991 another two RRR280 cavities and a computer controlled path length adjustment for both recirculations were installed. Since August '91 the accelerator produced cw-electron beam of energies up to 84 MeV (limited by the capacity of the He-refrigerator) which is used for different experiments including the commissioning of the FEL. Operational experience and experimental results are reported.

## 1 THE ACCELERATOR AND ITS PRESENT STATUS

The S-DALINAC has gone into operation at the end of 1990 when for the first time an electron beam was recirculated and reaccelerated twice and a maximum energy of 75 MeV was obtained. Since then the amount of beam time for different atomic, nuclear physics and free-electron laser physics experiments is on a remarkable increase and the maximum energy, achieved in August '92, raised to 104 MeV [1]. Figure 1 gives a general layout of the accelerator, its design parameters are summarized in Tab. 1 below.

In the upper right part of Fig. 1 the 270 keV injection can be seen where a dc electron beam produced by the electron gun is electrostatically preaccelerated and chopped as well as bunched in order to get the micro structure needed for acceleration in the rf linac. Here a 3 GHz continuous wave structure can be produced as well as a subharmonic micro structure as it is used for FEL operation (see Sect.

4 below). This section is followed by the superconducting injection linac formed by a short cryomodule, housing the 5-cell capture section, and a standard cryomodule containing two 20-cell acceleration cavities. An isochronous 180° beam transport system allows the beam from the injector to enter the main linac (center of Fig. 1) at energies up to 10 MeV. The superconducting main linac consists of four cryomodules, containing two 20-cell cavities each. The right part of the layout shows the 180° bends of the two recirculating beamlines. Their straight sections lead to the two corresponding bends, where the recirculated beams are combined and reinjected into the main linac via a four magnet chicane. Extraction of the beam to the experimental area is performed using the splitting dipole magnet just behind the main accelerator.




Fig. 1 S-DALINAC / FEL facility

For the FEL project [2,3], the present beam transport system of the accelerator is extended by a bypass to the first recirculation. The straight section of this bypass includes the undulator and passes into the 15 m long optical resonator with its mirror chambers at each end. An optical beam transport system extracts the laser beam to an experimental area outside the accelerator hall.

Table1: Design parameters of the S-DALINAC

Beam Energy / MeV	10–130
Energy Spread / keV	$\pm 13$
CW Current / $\mu\text{A}$	$\geq 20$
Operating Frequency / MHz	2997
Number of Structures (1m)	10
Capture Section (0.25m)	1

\*Supported by BMFT under contract number 06 DA 184 I and 05 345 EA I 3.

## 2 BEAM UTILIZATION

Since its completion the accelerator has produced many hours of beam time for accelerator test runs but mainly for different nuclear and atomic physics experiments.

At energies below 10 MeV the production of channeling radiation [4] and nuclear resonance fluorescence experiments ( $\gamma, \gamma'$ ) [5] are carried out behind the injection linac. Since summer 1991 a high energy beam (30 - 86 MeV) was delivered for first elastic (e,e) and inelastic (e,e') electron scattering experiments which were used to calibrate a new spectrometer (QCLAM). Subsequent to the calibration first coincidence measurements (e,e'p) could be carried out. At energies between 65 and 72.5 MeV the production of channeling radiation as a function of the crystal temperature was studied in a collaboration with the MPI Munich. For the first time the polarization of channeling radiation was measured in a scattering experiment.

Single pass operation for FEL experiments at about 30 MeV also started. We could study the production of synchrotron radiation i.e. spontaneous emission, the whole experimental setup was tested, and the optics including a 50 m long transfer line for the produced near-infrared light were aligned. The next FEL run will be used to examine the spectral distribution of the spontaneous emission and to test the subharmonic injection (see Sect. 4).

The maximum energy obtained in an accelerator test run was 104 MeV. Here the accelerator was operated with 50% duty factor (limited by the refrigeration power of 100 W) at a pulse duration of about one second. The achieved energy of 104 MeV is not limited by the cavities' field gradient (see Sect. 3) but only by the Helium refrigerator.

## 3 OPERATIONAL EXPERIENCE AND DEVELOPMENTS

During the beam time for atomic and nuclear physics experiments we gained precious experience in operating the superconducting cavities and its frequency tuners [6]. Eleven cavities as well as the normalconducting chopper/prebuncher system can now be operated reliably, especially since the magnetostrictive fine and motor driven coarse tuners are part of the computer controlled rf system (see below). A detailed description of the rf system and a comparison with other accelerators' systems is given in [7].

The present installation contains quite different superconducting cavities made from niobium of different purity ranging from RRR = 30 to RRR = 280. The according performance data are given in [1]. The average accelerating field measured with electron beam amounts to 5.9 MV/m which is well above the designed accelerating gradient of 5 MV/m. The highest gradient (10.1 MV/m) measured by the energy gain of the electron beam is remarkable, since at present such results are rather exceptional. For a reliable operation of superconducting cavities one has to consider a reduction in the accelerating field of

at least 10%. Here detuning due to radiation pressure and ponderomotive effects [7] are not taken into account.

In order to recirculate the beam from the main linac and to reaccelerate it another time two requirements have to be fulfilled: i) the energy of the recirculated beam has to be five times the energy of the injector beam because the last magnet of the chicane is identical with the last magnet of the 180° bend for the beam from the injector and ii) the phase of the recirculated beam has to match the phase of the injector beam. First attempts to accelerate the electron beam twice [8] or even three times, followed by the calculation of the phase slippage which the injector beam undergoes in the first main linac cavities, led to the construction of a system for adjusting the path length of the recirculating beam transport systems. The phase slippage too strongly depends on the injector beam energy which means that keeping the recirculation length unchanged is impossible. Therefore single magnets or groups of beam transport devices are mounted on linear bearings which are driven by computer controlled synchron motors. For both recirculations a change in the path length of more than 180° with respect to the accelerator frequency of 3 GHz is possible. TRANSPORT [9] calculations showed that only slight changes in the settings of the quadrupoles are required. Without a path length adjustment the successful operation of the S-DALINAC as a recirculating machine would not have been possible.

While commissioning the accelerator control of all beam transport devices and all beam diagnostics as well as of the electron gun was carried out by a local computer system. Since then a much more reliable system has been developed which includes the rf cavity-control and allows for a quite comfortable remote control of the S-DALINAC. Figure 2 gives the functional diagram.




Fig. 2 S-DALINAC control system

The controller for more than 150 power supplies for dipole and quadrupole magnets and for steering coils, a multi-channel ADC, a control unit for eight Faraday cups, and the selection of view screens used for beam diagnostics and the corresponding TV cameras is handled by an LSI 11/73. Hardware adapted programs interface between the

different devices and a common data block which can be controlled by local software or using Ethernet from the remote control room. There two workstations build a graphical user interface and two groups of four knobs each can be assigned to any beam transport device.

The rf-control system, in detail described in [10], consists of a 68020 microprocessor board build in house which is directly connected to 12 rf-control channels of the accelerating cavities and the driver for their tuners via VME-bus. The same microprocessor board acts as an interface to the electron gun control in the high voltage terminal. The connection is realized by a light link. Again either local software allows for operating the rf-system and the electron gun or remote control is possible using a more comfortable user interface, including another group of four knobs assignable to all relevant parameters of the rf-control circuits. For program development and long time storage of machine settings the remote control is part of the laboratory computer cluster.

#### 4 FURTHER DEVELOPMENTS

While completing the accelerator with its recirculations a free-electron laser in the near-infrared region was set up; details are reported in [2,3] and [11] includes a status report. Utilization of the electron beam accelerated in single pass operation yields laser wavelengths between 6 and 2.5  $\mu\text{m}$  corresponding to electron beam energies of 35 to 50 MeV. The modifications of the accelerator, necessary for the operation of the FEL have been carried out. A modified high current injector consisting of a pulsed electron gun and a subharmonic 600 MHz chopper / pre-buncher system has been designed, tested separately and installed at the linac [3].

The subharmonic 600 MHz system uses a frequency generator, phase locked to the accelerator's frequency standard, as a reference for two rf-control circuits (chopper and prebuncher). The principle function is identical to the circuits of the superconducting cavities [10].

For FEL operation the electron gun is pulsed with the 300th subharmonic ( $\hat{=}$  10 MHz) which together with an additional macro structure on the produced electron beam and together with the 600 MHz chopper yields a quite flexible system. While in cw FEL operation every 300th rf-bucket is filled corresponding to electron peak currents of 2.7 A, in cw nuclear physics operation electrons are accelerated in every rf period; here the beam current is 20  $\mu\text{A}$  ( $\approx$  3.6 mA peak current). Inbetween there exists a wide variety in time structure only limited in the combination of peak current and macro pulse length with respect to the acceptable energy spread. Limits are set by the time constants of the rf-control circuits and of the superconducting cavities themselves. Using the 600 MHz chopper as well as the 3 GHz chopper at the same time, another feature enlarges the variety: every 5th rf-bucket can be filled or two out of five rf-periods can be used for acceleration.

Besides the production of laser light in the near-infrared, the cw FEL operation gives the opportunity to investigate the excitation and propagation of higher order modes (HOM) as it is interesting with respect to future linear colliders. With its 5 pC per bunch and 100 ns time spacing the induced rf-power per cavity will be about 0.1 % of that in a linear collider cavity. A first estimate yields rf-power in the order of a few mW which allows for measuring the spectral distribution up to about 20 GHz. The propagation of HOM power is also accessible using the rf-couplers of all superconducting cavities. Because of the possible macro structure the HOM external quality factor can be measured by changing the beam duty factor. Thus the S-DALINAC operated in the FEL mode seems to be a highly suitable tool with respect to accelerator development and some aspects of linear collider studies.

#### 5 ACKNOWLEDGEMENT

We are much indebted to H. Lengeler for fruitful discussions and his continuous support. Stimulating discussions with E. Haebel, D. Proch and T. Weiland have been very helpful in the course of the project. We are very grateful for the tremendous help provided by H. Gaiser and the galvanic workshop at the GSI Darmstadt.

#### 6 REFERENCES

- [1] J. Auerhammer et al., Proc. Fifth Workshop on RF Superconductivity, Hamburg, Germany (1991), in press.
- [2] K. Alrutz-Ziemssen et al., Nucl.Instr.Meth. A304 (1991) 159.
- [3] K. Alrutz-Ziemssen et al., Nucl.Instr.Meth. A304 (1991) 300.
- [4] H. Genz et al., Appl.Phys.Lett. 57(27), (1990) 2956.
- [5] W. Ziegler et al., Phys.Rev.Lett. 65, (1990) 2515.
- [6] K. Alrutz-Ziemssen et al., Proc. Fourth Workshop on RF Superconductivity, KEK 89-12, Tsukuba, Japan (1990) 53.
- [7] H.-D. Gräf, Proc. Fifth Workshop on RF Superconductivity, Hamburg, Germany (1991), in press.
- [8] K. Alrutz-Ziemssen et al., Proc. of the 1990 Linear Acc. Conference, LA-12004-C, Los Alamos, NM, USA (1990) 626.
- [9] K.L. Brown et al., TRANSPORT, CERN 89-04 (1980).
- [10] H.-D. Gräf and A. Richter, Proc. of the 1988 Linear Acc. Conference, CEBAF 89-001, Williamsburg, VA, USA (1989) 231.
- [11] J. Auerhammer et al., 13<sup>th</sup> Intern.Conf. on FEL, Santa Fe, NM, USA (1991), in press.