© 1993 IEEE. Personal use of this material is permitted. However, permission to reprint/republish this material for advertising or promotional purposes or for creating new collective works for resale or redistribution to servers or lists, or to reuse any copyrighted component of this work in other works must be obtained from the IEEE.

STUDY OF A DETUNED ACCELERATING SECTION WITH THE COMPUTER PROGRAM *PROGON*^{*}

S. A. Heifets, S. A. Kheifets

Stanford Linear Accelerator Center, Stanford University, Stanford, CA 94309 USA

Abstract

The longitudinal coupling impedance for a number of lower passbands, bunch to bunch energy variation due to longitudinal wake fields, the beam loading compensation, some effects of production errors, and the rf pulse transmission through a detuned disk loaded accelerating section with finite wall conductivity have been studied using the computer program *PROGON*.

MOTIVATION AND METHOD

The detuned accelerating section [1] designed to diminish the undesirable effects of the transverse wake field has been studied previously using approximate methods. [2] [3] Here these results are confirmed by employing the new computer code PROGON [4] which is based on the field matching technique for the Fourier harmonics of the longitudinal electromagnetic (EM) travelling waves. The geometry of the considered 204 cell section is presented in Fig. 1a.



Figure 1. (a) The radii of the Nth cavity b(N) and iris a(N) for the considered 204 cell section. The gaps g(N) = 0.729 cm, the iris thicknesses l(N) = 0.149 cm. (b) The stored energy in the Nth cell W(N). (c) The relative group velocity in the Nth cell $v_g(N)/c$.

ACCELERATING FIELD

First, the EM fields in the structure, the corresponding stored energy W(N) per cell and the power flow $S_2(N)$ through the cavity cross section are found. These quantities define the relative group velocity $v_g/c = S_z d/W$, where d is the cell length. The stored energy W and the group velocity v_g are plotted in Figs. 1b,c, respectively.

ERRORS AND DAMPING

Next, the effect of fabrication errors for infinite and finite wall conductivity on the excitation of and propagation through the section of a cylindrical accelerating wave with frequency f has been studied. The absolute values of the reflection R(f) and the transmission T(f) coefficients are plotted in Fig. 2 for 'small' relative random radii cr-



Figure 2. The absolute values of the reflection R(f) and the transmission T(f) coefficients: (a),(b) 'small' relative random radii errors in the range $\Delta a/a = \Delta b/b =$ $\pm 2.5 \cdot 10^{-4}$: (c).(d) 'large' errors $\Delta a/a = \Delta b/b =$ $\pm 2.5 \cdot 10^{-3}$: (e).(f) the finite conductivity of the copper walls.

[★] Work supported by Department of Energy contract DE-AC03-76SF00515.



Figure 3. The real part of the longitudinal coupling impedance $Z_c(f)$ for a few lowest passbands.



Figure 4. (a) The envelopes of the rf pulse at the entrance (dashed curve) and exit (solid curve); (b) The energy gain by a bunch in an accelerating wave with power 70.56*MW* (curve 1), the energy loss due to wake fields of the previous bunches (curve 3) and their difference (curve 2) versus the bunch number. The number of electrons is $N_p = 0.7 \cdot 10^{10}$ per bunch. (c) A close up of part of curve 2 in Fig. 4b. (d) The effect of the random bunch population in the range $\Delta N_p/N_p = \pm 3\%$. This plot was obtained using ten different sets of random numbers for the same conditions as in Fig. 4b,c.

rors (Figs. 2a,b), for 'large' errors (Figs. 2c,d), and for the copper wall conductivity (Figs. 2e,f) without errors.

COUPLING IMPEDANCE

The real part of the longitudinal coupling impedance $Z_c(f)$ is presented in Fig. 3 for a few lower passbands.

PULSE TRANSMISSION

The distortion of an rf pulse transmitted through the detuned section with finite wall conductivity is illustrated in Fig. 4a where the envelopes of the rf pulse at the entrance (dashed curve) and the exit (solid curve) are plotted [5].

BEAM LOADING

The beam loading [6] for a long train of bunches is illustrated in Fig. 4b [7]. The energy gain by a bunch in an accelerating wave with power 70.56 MW (curve 1), the energy loss due to wake fields of the previous bunches (curve 3) and their difference (curve 2) are plotted versus the bunch number for the number of electrons $N_p = 0.7 \cdot 10^{10}$ per bunch. The impedance of the first passband only is taken into account for the wake field calculations. Fig. 4c is a close up of part of curve 2 in Fig. 4b. Fig. 4d illustrates the effect of the random bunch population in the range $\Delta N_p/N_p = \pm 3\%$.

ACKNOWLEDGEMENTS

We are grateful to K. Bane, R. Miller, R. Ruth and J. Wang for useful discussions.

REFERENCES

- J.W. Wang, B.W. Littmann, "Design Study on Quasi-Constant Gradient Accelerating Structure," SLAC/AP-32, 1991.
- 2. R. Helm, "Computation of the properties of traveling-wave linac structures," SLAC-PUB-813 (1970).
- 3. K. Thompson, R. Ruth "Controlling Transverse Multi-bunch Instabilities in Linacs," Phys. Review D41, 964 (1990).
- S.A. Heifets, S.A. Kheifets "Longitudinal Electromagnetic Fields in an Aperiodic Structures," SLAC-PUB-5907, 1992.
- 5. S.A. Heifets, S.A. Kheifets "RF Pulse Transmission through an Accelerating Section," SLAC Note AAS-74, September 1992.
- R. Ruth, "Multi-bunch Energy Compensation," SLAC-PUB-4541, 1988.
- S.A. Heifets, S.A. Kheifets "Study of the Energy Gain and the Beam Loading of the Detuned Structures with a Simple Model," SLAC/AP-96, January 1993.